



CHANGING A PANEL BATTERY

Lynx

You will need a flat head and Phillips head screwdriver.

STEP
1

PLACE YOUR SYSTEM ON TEST

Before changing the batteries, log into your [Guardian account](#) or call **1.800.PROTECT** (1.800.776.8328) to place your system on Test Mode.

This ensures Guardian doesn't accidentally notify the authorities.

STEP
2

LOCATE YOUR PANEL BOX

Locate your control panel and use a Phillips head screwdriver to remove the locking screw at the top of the panel.

ACCESS YOUR BATTERY

Insert the flat head screwdriver into the slots at the top of the panel. There is one slot on the left and one slot on the right. You may need to gently twist the screwdriver to help separate the cover. Be careful not to force the panel open.



PLEASE NOTE: Your security system may sound or the panel may emit a tamper beeping tone as an indication that the battery has been removed from the system. You may need to disarm the system after opening the panel to silence the tamper beeping tone.

STEP
3

DISCONNECT THE BATTERY

Now that the panel is open, follow the wires from the battery pack to the connector and unplug it from the panel.

Remove the screws that secure the battery retainer (Phillips head screwdriver required). Next, remove the battery retainer, and then remove the battery pack.

STEP
4

CONNECT NEW BATTERY

Insert the new battery and plug it into the panel. Be sure to feed the battery wires through the three routing clips. Depending on the size of the replacement battery, it will connect to either the two- or three- position connector.

Once the new battery is in place, reconnect the battery retainer. Carefully swing the panel up to the mounting plate and lock it into place.

Next, plug the AC adapter into the plug outlet and replace the retaining screw. The Low Battery indicator will clear from the screen automatically once the AC power is restored.

STEP
5

TEST YOUR SYSTEM

Test your system to make sure everything is working properly.

Return to your online Guardian account or contact us at **1.800.PROTECT** (1.800.776.8328) to verify the test signals and to remove your system from **Test Mode**.

NOTE

DATE & TIME RESET

If you use MyGuardianHome.com: The date and time will reappear within one hour and the weather will reappear within 24 hours. If the items do not reappear on your keypad after 24 hours, please contact us at **1.800.PROTECT** (1.800.776.8328).



FOR ASSISTANCE, CALL **1.800.PROTECT** (1.800.776.8328)
OR VISIT guardianprotection.com/support.